ELECTRICAL DESIGN GROUP
ELECTRICAL BUILDING SERVICES CONSULTANTS
P.O. Box 15, SHERWOOD Q. 4075
Phone: (07) 3278 4375
Website: www.edg.net.au Email: brisbane@edg.net.au

C3599a - TI-TREE COLLECTIVE **C3599a-0005(C).xls**
DISTRIBUTION BOARD DB-P
REVISION C - 28 APRIL 2026

				REV
FAULT CURRENT:	6KA	MAIN SWITCH:	100A NON AUTO LOAD BREAK	A
CHASSIS SIZE:	30 POLE	SUPPLIED FROM:	MSB	A
CHASSIS RATING:	250A	SUPPLY CABLE:	4C+E 16	C
PHASES:	3			A
PROVIDE THE DB WITH A FULL WIDTH EMPTY DIN RAIL TO ACCOMMODATE FUTURE CONTACTORS AND CONTROLS. REFER TO THE NOTES FOR ADDITIONAL REQUIREMENTS				A

CIRC	PH	CIRCUIT BREAKER (amps)	CONTROL EQUIPMENT	CABLE SIZE (mm^2)	LOCATION	CIRCUIT USE	
P1	1	20	RCBO	2.5	BASEMENT	GPO	A
P2	1	20	RCBO	2.5	BASEMENT	COMMUNICATIONS	A
P3	1	20	RCBO	2.5	BASEMENT	JACKING PUMP	A
P4	1	20	RCBO	2.5	BASEMENT	GPO	A
P5	1	20	RCBO	2.5	BASEMENT	POOL	C
P6	1	20	RCBO	2.5	BASEMENT	POOL	C
P7	1	20	RCBO	2.5	BASEMENT	IRRIGATION	B
P8	3	20	RCBO	2.5	BASEMENT	RSD	A
P9	1	20	RCBO	2.5	RISER	MATV / RISER	B
P10							C
P11							C
P12							C
P13							C

ELECTRICAL DESIGN GROUP BRISBANE PTY LTD ACN 092 710 793
TRADING AS – ELECTRICAL DESIGN GROUP ABN 96 092 710 793