



ELECTRICAL DESIGN GROUP

ELECTRICAL BUILDING SERVICES CONSULTANTS

P.O. Box 15, SHERWOOD Q. 4075

Phone: (07) 3278 4375

Website: www.edg.net.au Email: brisbane@edg.net.au

C3599a - TI-TREE COLLECTIVE

C3599a-0011(B).xls

DISTRIBUTION BOARD DB-5

REVISION B - 28 APRIL 2025

							REV
FAULT CURRENT:		6KA	MAIN SWITCH:		100A NON AUTO LOAD BREAK		A
CHASSIS SIZE:		48 POLE	SUPPLIED FROM:		MSB		A
CHASSIS RATING:		250A	SUPPLY CABLE:		4C+E 16		A
PHASES:		3					A
REFER TO THE POWER SCHEMATIC FOR DETAILS OF CIRCUITS P1 AND P2. PROVIDE THE DB WITH SURGE PROTECTION. REFER TO THE NOTES FOR ADDITIONAL REQUIREMENTS							A
CIRC	PH	CIRCUIT BREAKER (amps)	CONTROL EQUIPMENT	CABLE SIZE (mm ²)	LOCATION	CIRCUIT USE	A
P3	1	32	RCBO	6.0	KITCHEN	COOK TOP	A
P4	3	32	RCBO	6.0		HWS	A
P5	1	40	RCBO	6.0	KITCHEN	OVEN	B
P6	3	40	RCBO	6.0		HWS	B
P7	1	20	RCBO	2.5		POOL	B
P8	1	20	RCBO	2.5		GPO	A
P9	1	20	RCBO	2.5		GPO	A
P10	1	20	RCBO	2.5		GPO	A
P11	1	20	RCBO	2.5		GPO	A
P12	1	20	RCBO	2.5		GPO	A
P13	1	20	RCBO	2.5		GPO	A
P14	1	20	RCBO	2.5		GPO	A
P15	1	20	RCBO	2.5		GPO	A
P16	1	20	RCBO	2.5		GPO	A
P17	1	20	RCBO	2.5		GPO	A
P18	1	20	RCBO	2.5		GPO	A
							A
							A
							A
L1	1	20	RCBO	2.5		LIGHTS	A
L2	1	20	RCBO	2.5		LIGHTS	A
L3	1	20	RCBO	2.5		LIGHTS	A
L4	1	20	RCBO	2.5		LIGHTS	A
L5	1	20	RCBO	2.5		LIGHTS	A
L6	1	20	RCBO	2.5		LIGHTS	A
							A
							A
							A
							A