

ELECTRICAL DESIGN GROUP

ELECTRICAL BUILDING SERVICES CONSULTANTS

P.O. Box 15, SHERWOOD Q. 4075 Phone: (07) 3278 4375 Fax: (07) 3716 0222 Web Site: www.edg.net.au Email: brisbane@edg.net.au

C3051a - ASPLEY LEAGUES CLUB - RUGBY AMENITIES DISTRIBUTION BOARD DB-A

C3051a-0004(A).xls

REVISION A - 24 JULY 2023

	OIOI1 A	2+ 00L1 2020									
							REV				
	FAULT CURRENT: 6KA MAIN SWITCH: 250A NON AUTO BREAK CHASSIS SIZE: 60 POLES SUPPLIED FROM: MSB						А				
		CHASSIS SIZE:	60 POLES		SUPPLIED FROM:	MSB	Α				
CHASSIS RATING: 250A SUPPLY CABLE: 1C 95						1C 95	Α				
		PHASES:	3				Α				
PROVIDE THE DB WITH A FULL WIDTH EMPTY DIN RAIL TO ACCOMMODATE FUTURE CONTACTORS AND CONTROLS IN ADDITION TO THE INITIAL CONTROL PROVIDE THE DB WITH AN AS2293 EMERGENCY LIGHTING CONTROL SYSTEM TO CONTROL THE ASSOCIATED EMERGENCY LIGHTS. PROVIDE THE DB WITH SURGE PROTECTION. PROVIDE A SHOP DRAWING OF THE DISTRIBUTION BOARD FOR APPROVAL.											
CIRC	PH	CIRCUIT	CONTROL	CABLE	LOCATION	CIRCUIT					
		BREAKER (amps)	EQUIPMENT	SIZE (mm ²)		USE					
P1	1	20	RCBO	2.5	PLATFORM	GPOs	Α				
P2	1	20	RCBO	2.5	PLANT	CR-A	Α				
			2020								

CIRC	РН	CIRCUIT BREAKER (amps)	CONTROL EQUIPMENT	CABLE SIZE (mm ²)	LOCATION	CIRCUIT USE	
P1	1	20	RCBO	2.5	PLATFORM	GPOs	Α
P2	1	20	RCBO	2.5	PLANT	CR-A	Α
P3	1	20	RCBO	2.5	PLANT	GPOs	Α
P4	1	20	RCBO	2.5	FIRST AID	GPOs	Α
P5	1	20	RCBO	2.5	SOUTH AMENITY	GPOs	Α
P6	1	20	RCBO	2.5	SOUTH AMENITY	HAND DRYER	Α
P7	1	20	RCBO	2.5	NORTH AMENITY	GPOs	Α
P8	1	20	RCBO	2.5	NORTH AMENITY	HAND DRYER	Α
P9	1	40	RCBO	6.0	FIRST AID	HWS	Α
P10	1	20	RCBO	2.5	AMENITY	GPOs	Α
P11	1	20	RCBO	2.5	AMENITY	HAND DRYER	Α
P12	3	20	RCBO	2.5	SOUTH EXTERNAL	3 X 4.8KW HWS	Α
P13	3	20	RCBO	2.5	SOUTH EXTERNAL	3 X 4.8KW HWS	Α
P14	3	20	RCBO	2.5	NORTH EXTERNAL	3 X 4.8KW HWS	Α
P15	3	20	RCBO	2.5	NORTH EXTERNAL	3 X 4.8KW HWS	Α
L1	1	20	RCBO	2.5	AMENITY	1200 BATTEN LIGHTS	A
L2	1	20	RCBO	2.5	CENTRAL ROOMS	LIGHTS	Α
L3	1	20	RCBO	2.5	SOUTHERN SIDE	LIGHTS	А
L4	1	20	RCBO	2.5	NORTHERN SIDE	LIGHTS	Α