

Quartz Heat Lamp Assemblies



The stylish and functional Roband quartz heat lamp assemblies provide a balance of heat and light to front or back of house applications. They are manufactured from extruded anodised aluminium, with a number of different sizes and options available to suit various requirements. All models come with a standard mount bracket. Optional mount kit is also available. See page 60 for details.

Designed by Roband Australia, Easy Fit Globes feature a protective quartz outer layer that encapsulates the inner globe allowing for easier handling. This secondary layer of glass also protects food from globe breakages by capturing the shards and eliminating the need for a traditional glass window in the base of the cover. *Lamp replacement can now be performed without the need for an electrician and takes only seconds.*

Standard Models

The standard heat lamp assemblies (e.g. HQ450E) come **with** a control box that houses the isolating on/off switch. They also feature a simple mounting system and come complete with a 10 Amp plug and cord.

Fabricator Models

The heat lamp assemblies are also available **without** the control box and on/off switch (e.g. HUQ375E) so they can be connected to a remote switch setup. The removal of the control box shortens the length of the lamp assembly accordingly.

Standard mounting bracket available on standard and fabricator models



SPECIFICATIONS - STANDARD MODELS (INCLUDES CONTROL BOX)

| MODEL | INTERNAL LAMPS | MOUNT TYPE | CURRENT Amps | POWER Watts | LENGTH mm | LAMP CENTRES* | INCLUSIONS |
|---------|----------------|------------|--------------|-------------|-----------|---------------|---------------------|
| HQ450E | 1 lamp | Standard | 1.5 | 350 | 450 | N/A | Switch, plug & cord |
| HQ900E | 2 lamps | Standard | 3.0 | 700 | 900 | 400 | Switch, plug & cord |
| HQ1200E | 3 lamps | Standard | 4.6 | 1050 | 1200 | 345 | Switch, plug & cord |
| HQ1500E | 4 lamps | Standard | 6.1 | 1400 | 1500 | 345 | Switch, plug & cord |
| HQ1800E | 4 lamps | Standard | 6.1 | 1400 | 1800 | 400 | Switch, plug & cord |
| HQ2100E | 5 lamps | Standard | 7.6 | 1750 | 2100 | 400 | Switch, plug & cord |

*Length between centre of each lamp.



SPECIFICATIONS - FABRICATOR MODELS (NO CONTROL BOX)

| MODEL | INTERNAL LAMPS | MOUNT TYPE | CURRENT Amps | POWER Watts | LENGTH mm | LAMP CENTRES* | INCLUSIONS |
|--|----------------|------------|--------------|-------------|-----------|---------------|------------|
| COMPLETE WITH A, N & E WIRE IN PTFE 1700 MM LENGTH FOR INSTALLATION TO YOUR OWN CONTROLLER | | | | | | | |
| HUQ375E | 1 lamp | Standard | 1.5 | 350 | 375 | N/A | N/A |
| HUQ825E | 2 lamps | Standard | 3.0 | 700 | 825 | 400 | N/A |
| HUQ1125E | 3 lamps | Standard | 4.6 | 1050 | 1125 | 345 | N/A |
| HUQ1425E | 4 lamps | Standard | 6.1 | 1400 | 1425 | 345 | N/A |
| HUQ1725E | 4 lamps | Standard | 6.1 | 1400 | 1725 | 400 | N/A |
| HUQ2025E | 5 lamps | Standard | 7.6 | 1750 | 2025 | 400 | N/A |

*Length between centre of each lamp.



Showing wire guard open for easy replacement of the globe



Dimensions for all standard quartz and fabricator quartz lamps (HQ & HUQ models). Brackets are removable.

